PowerProducts™

| LMR BATTERY SPECIFICATIONS | PART NUMBER |
|---|---|
| | **BP5447MH** |

| | |
|---|---|
| COMPATIBLE RADIOS | Motorola MT1000, MTX800, MT900 |
| REPLACES OEM BATTERY | NTN5447BR |
| COMPATIBLE CHARGERS | Endura EC1-MT5A, EC1M-MT5A, EC6M-MT5A |
| VOLTAGE | 10.0V |
| CAPACITY | 2000 mAh |
| CHEMISTRY | NiMH |
| CELL TYPE | FDK, Panasonic, or equivalent |
| OPERATING TEMPERATURE | -10° C to +65° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES | 500 |
| CHARGE TYPE | Rapid or trickle |
| CONDITIONER COMPATIBLE | Yes |
| THERMAL PROTECTION | Yes |
| HOUSING MATERIAL | ABS |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | N/A |
| WARRANTY | 12 months |
| PRODUCT PHOTO |  Dimensions (W x H x D) 2.64” x 3.39” x 1.38” |

Telephone **770-740-9400** • 2170 Brandon Trail, Alpharetta, GA 30004 • Fax **770-569-1844**